



Agilent Technologies 5348A 26.5 GHz Microwave Counter/Power Meter

Data Sheet

Input 1

Frequency Range: 500 MHz to 26.5 GHz

Sensitivity

500 MHz - 12.4 GHz: -32 dBm (-35 dBm typical)

12.4 GHz - 20.0 GHz: -27 dBm (-32 dBm typical)

20.0 GHz - 26.5 GHz: -20 dBm (-27 dBm typical)

Maximum Input: +7 dBm

Damage Level: +25 dBm, peak

SWR

500 MHz - 12.4 GHz: <2:1 typical

12.4 GHz - 20.0 GHz: <3:1 typical

20.0 GHz - 26.5 GHz: <3:1 typical

Accuracy: ± 1 LSD \pm time base error x frequency

Resolution: 1 Hz or 10 kHz, selectable

Optional Increased Damage Level Option 006

Protects Input 1 from damage by limiting high level signals.

All specifications are the same except Input 1.

Damage Level

500 MHz to 6 GHz: +39 dBm (8 watts)

6 GHz to 18 GHz: +36 dBm (4 watts)

18 GHz to 26.5 GHz: +34.8 dBm (3 watts)

Sensitivity reduced by

3 dBm, 500 MHz to 12.4 GHz

4 dBm, 12.4 GHz to 20.0 GHz

5 dBm, 20.0 GHz to 26.5 GHz

Input 2

Frequency Range: 10 Hz - 525 MHz

Sensitivity: 25 mV rms (15 mV rms typical)

Impedance: 1 Mohm nominal shunted by <70 pF (10 Hz to 80 MHz) or 50 Ω nominal (10 MHz to 525 MHz)

Damage Level: 50 V or 1 M V

dc - 5 kHz: 250V (dc + ac peak)

>5 kHz: 5.5V rms (+28 dBm) + 1.25×10^6 V rms/FREQ

Accuracy: ± 1 LSD $\pm [(1.4 \times \text{Trigger Error/Gate Time}) \pm \text{Time Base Error}] \times \text{frequency}$

Resolution: 1 Hz or 10 kHz, selectable

Automatic Amplitude Discrimination

Automatically measures the largest of all signals present, provided that signal is >6 dB (typical) above any signal within 500 MHz; >20 dB (typical) above any signal within 500 MHz to 26.5 GHz.

Tracking Speed

Resolution = 1 Hz, Speed = 1 MHz/sec

Resolution = 10 kHz, Speed = 1 GHz/sec

Acquisition Time

Resolution = 1 Hz, Time = <125 ms

Resolution = 10 kHz, Time = <60 ms

Maximum Deviation

20 MHz p-p, Automatic mode

60 MHz p-p, Manual mode (via HP-IB only)

Maximum FM Rate: 10 MHz

AM Tolerance: Any modulation index provided the minimum signal level is not less than the sensitivity specification.

Power Meter Specifications

Frequency Range: 0 MHz to 26.5 GHz, sensor dependent

Power Range: -70 to +20 dBm (100 pW to 100 mW), sensor dependent

Dynamic Range: 50 dB in 10 dB steps

Resolution: 0.01 dB in logarithmic mode, 0.1% of full scale in linear mode.

Auto Filter: The meter automatically selects the required number of averages for the selected range.

Accuracy

Instrumentation: ± 0.02 dB or $\pm 5\%$

Zero Set (digital settability of zero): $\pm 5\%$ of full scale on most sensitive range. Decrease percentage by a factor of 10 for each higher range, ± 1 display count.