

# BRUEL & KJAER 2230 SOUND LEVEL METER

The 2230 Sound Level Meter is an IEC Type 1 (Impulse) instrument for environmental certification and factory noise investigations, including cyclical, fluctuating, and impulsive noise measurement, as well as assessment of the risk of hearing damage.

## FEATURES

- A-, C-, Lin. and All Pass weighting
- Five measuring modes
- RMS Fast, Slow, Impulse, and Peak response
- 24 to 130 dB
- 4-digit LCD updated every second. 0.1 dB resolution
  
- **Power Source:** Int. battery supply (4 x "AA" batteries)

## APPLICATIONS

Designed for accurate, everyday calibration of sound level meters, etc., using .5 in. and 1 inch microphones.

## ACCESSORIES

Shipped with the following items: Instrument shipping case, 4230 Sound Level Calibrator, 1625 Octave Filter, instrument manual, foam windsock, eight spare "AA" batteries, recorder output cable

## MANUFACTURER

**Bruel & Kjaer** – [www.bkhome.com](http://www.bkhome.com)

---

# BRUEL & KJAER 1625 1/3 OCTAVE FILTER FOR SOUND LEVEL METER

Third and full octave filter set for use with the Bruel & Kjaer 2230, 2231 and 2235 sound level meters..

## SPECIFICATIONS

<b>Calibrator Output:</b>	Provides 94 dB re 20 uPs sound level at 1 kHz.
<b>Calibration Accuracy:</b>	+/- 0.0 dB
<b>Power Source:</b>	Int. battery supply (4 x "AA" batteries)